

## CAUTIONS

- Before first use, please check carefully for any possible damage caused in transportation.
- Before any maintenance, please confirm the power is off.
- Please do not disconnect or install the panel by non-professional individuals.
- Avoid falling or placing heavy objects on the panel.
- Please do not let the panel be exposed to rain or moisture, to avoid circuit problem.
- Please do not use the panel with overloaded voltage and/or current.
- Keep the panel out of the reach of children



## Mini LED Panel EX80

### User Manual



## 📌 OVERVIEW

EverSirius powerful Mini LED panel EX80 is popular for its excellent appearance and performance. It includes DMX XLR 5pins in/out. Both CRI and TLCI are 95+. EX80 is the winner of NRK(Norwegian national broadcaster)' RFQ in 2019, due to its compact size, high light output, exact color, high-grade quality and DMX512 control. Perfect assistant for studios, broadcasting, and field shooting.

## 📌 SPECIFICATIONS

Model	EX80
Power	80W
CRI	Ra 95-98
TLCI	> 95
CCT	Bi-Color 3200K-5600K
Light source	450 pcs DIP LED
Dimmer	0~100% step-less dimming
Beam angle	60°
Working voltage	AC 100-240V, 50-60Hz / DC 12-17V
Dimension	41.9 x 43.8 x 7.7 cm (with barndoor)
Weight	3.14 kg
Working Temperature	-20°C ~ +45°C

## 📌 WHAT ARE INCLUDED

1. LED Panel EX80 ×1
2. DMX XLR 5pins cable ×1
3. AC adapter ×1
4. Power cable ×1
5. Barn doors ×1 set
6. Diffusion panel ×1
7. Safety cable ×1
8. Soft bag ×1

## 📌 INSTRUCTIONS

A brief introduction to facilitate your operation.



- ① **V-mount battery plate.** For the use of AC adapter and the battery.
- ② **Power switch.**
- ③ **Power cable socket.**
- ④ **LCD Display.** When power is on, it shows the current brightness, color temperature, and DMX channel.
- ⑤ **Dimmer.** Rotate the knob for dimming.
- ⑥ **Color temperature adjustment.** Rotate the knob to adjust CCT.
- ⑦ **DMX connecting socket (out).**
- ⑧ **DMX connecting socket (in).**